1976-06

Computer prediction of tropospheric radio transmission loss for selected paths in the Pacific northwest

Cassidy, Richard Michael

COMPUTER PREDICTION OF TROPOSPHERIC RADIO TRANSMISSION LOSS FOR SELECTED PATHS IN THE PACIFIC NORTHWEST

Richard Michael Cassidy

NPS-32Ca 76061

NAVAL POSTGRADUATE SCHOOL
Monterey, California

THESIS

Computer Prediction of Tropospheric Radio Transmission Loss for Selected Paths in the Pacific Northwest

by

Richard Michael Cassidy, Jr.

June 1976

Thesis Advisor: J. B. Knorr

Prepared for:
Naval Torpedo Station
Keyport, Washington 98345

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) Computer Prediction of Tropospheric Radio Transmission Loss for Selected Paths in the Pacific Northwest		5. TYPE OF REPORT & PERIOD COVERED Master's Thesis June 1976
		6. PERFORMING ORG. REPORT NUMBER
7. AUTHOR(s) Richard Michael Cassidy, Jr.		8. CONTRACT OR GRANT NUMBER(s)
9. PERFORMING ORGANIZATION NAME AND ADDRESS Naval Postgraduate School Monterey, CA 93940		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
11. CONTROLLING OFFICE NAME AND ADDRESS Naval Postgraduate School Monterey, CA 93940		12. REPORT DATE June 1976
		13. NUMBER OF PAGES
14. MONITORING AGENCY NAME & ADDRESS(if different from Controlling Office) Naval Postgraduate School Monterey, CA 93940		15. SECURITY CLASS. (of this report) UNCLASSIFIED
		15a. DECLASSIFICATION/DOWNGRADING SCHEDULE

16. DISTRIBUTION STATEMENT (of this Report)

Approved for public release; distribution unlimited.

17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)

18. SUPPLEMENTARY NOTES

19. KEY WORDS (Continue on reverse side if necessary and identify by block number)

20. ABSTRACT (Continue on reverse side if necessary and identify by block number)

In order to characterize the propagation conditions along known paths at VHF and S Band frequencies, transmission loss predictions are produced by computer methods. An attempt is made to define the standard atmospheric conditions along these paths through the presentation of the statistics for normal and super-refractive propagation conditions.

DD FORM 1 JAN 73 1473 EDITION OF 1 NOV 65 IS OBSOLETE
S/N 0102-014-6601

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

NAVAL POSTGRADUATE SCHOOL
Monterey, California

Rear Admiral Ishan Linder
Superintendent

Jack Borsting
Provest

This thesis prepared in conjunction with research supported in part by Naval Torpedo Station, Keyport, Washington under work order N00253-76-WR-00025.

Released as a
Technical Report by:

Computer Prediction of Tropospheric Radio Transmission Loss for Selected Paths in the Pacific Northwest

by

Richard Michael Cassidy, Jr.
Lieutenant, United States Navy
A.B., University of North Carolina, 1970

Submitted in partial fulfillment of the
requirements for the degree of

MASTER OF SCIENCE IN ELECTRICAL ENGINEERING

from the

NAVAL POSTGRADUATE SCHOOL
June 1976

ABSTRACT

In order to characterize the propagation conditions along known paths at VHF and S Band frequencies, transmission loss predictions are produced by computer methods. An attempt is made to define the standard atmospheric conditions along these paths through the presentation of the statistics for normal and super-refractive propagation conditions.

TABLE OF CONTENTS

LIST OF TABLES

LIST OF FIGURES

ACKNOWLEDGMENT

I wish to express my appreciation to Mr. Herb Hitney of NELC for his kind assistance in providing the IREPS output used in this report.

I. INTRODUCTION

Numerous methods of estimating tropospheric propagation path loss are currently found in the literature. These include both graphical and computer techniques, of which the graphical methods are most widely presented. In conducting this particular study a program dealing with tropospheric path loss prediction (TROPOPLOT) was chosen as a computer method of analysis. This program was originally published by ESSA in a technical report [Ref. 6] and was subsequently modified for use at the Naval Postgraduate School [Ref. 7]. Tests were conducted by Longley and Reasoner [Ref. 8], in which the computer-predicted results of the program were compared with empirical data taken over a number of different paths. The results showed that TROPOPLOT can provide reasonably accurate predictions of path loss within certain constraints.

The paths selected for analysis in this study are located in the Puget Sound, Washington area. They comprise both existing and proposed communications links connecting the underwater range facilities operated by the Naval Torpedo Station at Keyport, Washington. The range operation centers are currently located at Winchelsea Island, British Columbia and on Zelatched Point near Dabob Bay. The present communications requirements include on-range communications with both range control vessels and the submarines and aircraft conducting tests, the capability to monitor telemetry information,

and the maintenance of telephone links with other sites. Proposals for expansion of the range facilities as the TRIDENT program progresses include possible at-sea range facilities and digital data transmission to a central computer processing center located at Bangor or Keyport. These proposals would increase the bandwidth requirements of the links and thus necessitate a change from the present VHF frequency range to an S-band (2 GHz) line of sight link.

The terminal and repeater sites are shown in Figure 1. The existing VHF link consists of paths from Winchelsea to Lookout Mt. (repeater) to Bangor and from Zelatched Point to Bangor. The proposed link at 2 GHz runs from Makah to Striped Peak (repeater) to Mt. Constitution (repeater) to Gold Mt. (repeater) to Bangor or Keyport, as well as from Zelatched Point to Bangor or Keyport. Each of these paths is computer-analyzed in Section II.

In addition to computing path loss, the historical meteorological data for this area was examined in an attempt to characterize the "typical" propagation conditions found in this vicinity. This was accomplished by means of the Integrated Refractive Effects Prediction System (IREPS) which provided output based on data taken from upper air sounding stations in the Puget Sound area. This information could also be useful in the determination of link service probability.



Figure 1

NAVTORPSTA Keyport Ranges and Vicinity

A listing of a computer program designed to plot path profiles and to aid in the determination of several input variables is included in the appendices, as is an explanation of the modifications required in order to use detailed terrain profile information in the TROPOPLOT program.

II. COMPUTER-AIDED PATH LOSS PREDICTION

A. PROGRAM DESCRIPTION

TROPOPLOT provides as an output a measure of the long-term attenuation over a given path. The program was primarily designed for use in cases where detailed terrain information was not available but can be used accurately with user-supplied data after a slight modification. The required input parameters include frequency, antenna heights, antenna gains, line losses, receiver sensitivity, path length, polarization, transmitter power out, surface refractivity, conductivity, permittivity, and a measure of the terrain roughness Δh. These parameters are for the most part well defined in Refs. 6 and 7 and are easily determined except in the case of user-supplied terrain profile information. For this sort of input there is some ambiguity concerning the selection of values for σ, ε, Δh, and the effective antenna heights.

In considering a path which includes both poor ground surfaces (ε=4, σ=.001) and sea water surface (ε=81, σ=5) the particular value to use as input is not specified, although a completely oversea path requires an adjustment to the program not available in the version used for this study. Thus the values of ε and σ chosen were based on the corresponding value for that portion of the terrain that constituted the largest portion of the dominant reflecting plane between the transmitter and receiver.

The path geometry considered is shown in Figure 2 and indicates $h_{gl,2}$ as the structural transmitter (receiver) height above ground. This input parameter is converted into an effective height, $h_{el,2}$ by the program. It should be noted that Longley and Rice consider two cases: one for random antenna siting in which structural heights, $h_{gl,2}$ are considered equal to the effective heights, $h_{el,2}$; and another in which the sites are carefully selected, as in the case of radio relay links, and the effective heights are larger than the structural heights as shown below:

$$h_{el,2} = h_{gl,2} + k\exp(-2h_{gl,2}/\Delta h) \text{ meters}$$

The variable k is considered to have a maximum value of 50 as determined by the author's study of varied terrain conditions. The method presented below for the computation of k is valid only for antenna heights less than or equal to 10 meters. In Callaghan's version [Ref. 7] this determination was:

$$k = 1 + 4\sin(\pi h_{gl,2}/10) \text{ for } 0 \leq h_{gl,2} \leq 5$$

$$= 5 \qquad \text{otherwise}$$

Since most of the antennas in the links under study had structural heights in the neighborhood of 50 meters, it is obvious that predictions based on strictly $h_{gl,2}$ would in this case, produce an erroneous (higher than normal) prediction of path loss. This factor is recognized by the authors as an area requiring better definition and as a primary source of



Figure 2
Path Geometry

prediction error. For this reason the modifications to TROPOPLOT which are detailed in Appendix B were necessary. The effect of varied antenna heights in the input of the unmodified program is shown in the output data presented later in this section.

The description of the terrain is accomplished by a statistical quantity, Δh, which is defined in Ref. 6 as "the asymptotic value of the interdecile range, $\Delta h(d)$, of terrain heights above and below a straight line fitted to elevations above sea level. The parameter $\Delta h(d)$ is calculated at fixed distances and its median value usually increases with path length to Δh." For a single path profile these definitions are not adequate. The asymptotic value, Δh, used in this study as determined by taking the interdecile range of the difference between a straight line fitted to the path profile points and the path profile points themselves. The results of this estimation of Δh correlate favorably with those values listed in Table 1 [Ref. 7] which shows estimated values of Δh for particular types of terrain. Figure 3 shows an example of the straight line fit to the terrain profile between Lookout Mt. and Bangor. The details of the computation are found in Appendix B.

Having thus considered the variations in the input parameters the program constraints should be noted. TROPOPLOT is designed for use within the following constraints:

	Zelatched Point to Keyport	Makah to Striped Peak	Lookout Mt to Keyport	Zelatched Point to Bangor	Mt Constitution to Gold Mt.	Striped Peak to Mt Constitution	Bangor to Gold Mt .	Keyport to Gold Mt.	Lookout Mt. to NOEF	NOEF to Gold Mt.	NOEF to Zelatched Point	Lookout Mt. to Bangor
TXPO watts	10 / 100	2 / 100	10 / 100	10 / 100	10 / 100	10 / 100	10 / 100	10 / 100	10 / 100	10 / 100	10 / 100	10 / 100
TAG=RAG db	31 / 12	31 / 12	31 / 12	31 / 12	31 / 12	31 / 12	31 / 12	31 / 12	31 / 12	31 / 12	31 / 12	31 / 12
FREQ MHz	2000 / 250	2000 / 250	2000 / 250	2000 / 250	2000 / 250	2000 / 250	2000 / 250	2000 / 250	2000 / 250	2000 / 250	2000 / 250	2000 / 250
DIST(km)	15	81.9	109.5	8.1	124.3	85.35	16.5	20.5	110.3	17.8	6.2	111.9
Δh(m)	57.43	171.72	87.86	59.96	140.68	208.99	80.25	96.52	120.6	67.67	40.87	103.61
TE1(rad)	1.466	-0.7505	-0.9075	1.3089	-1.1345	-.06981	.8552	1.256	-.90757	+.89012	1.3177	-.82030
TE2(rad)	1.3963	0.7505	1.2217	.244346	+1.1345	+.06981	-.8552	-.7505	.94248	-.89012	1.0646	.82030
HIG(m)	50	168.75	701.4	97.8	698.58	330	50	50	330	50	78	510.7
H2G(m)	50	200	50	50	250	700	286.75	362.5	50	200	120	50
DL1(km)	2.5	81.9	129	2	250	128.75	16.7	1.5	107.5	18	2.0	137.5
DL2(km)	2.5	81.9	7.5	6.25	250	128.75	16.7	20	31.25	18	4.3	137.5
ϵ	25.0	25	25	25	25	25	25	25	25	25	25	25
N_s N-units	308	298	297	307	292	299	306	301	297	308	308	306

Table I

Input Values for Various TROPOPLOT Runs



Figure 3

Examples of Least Square Line Fit to Terrain

Parameter	Range
frequency (f)	20 to 40,000 MHz
antenna height ($h_{gl,2}$)	0.5 to 3000 m
distance (dist)	1 to 2000 km
surface refractivity (N_s)	250 to 400 N-units

The antenna siting is subject to the following conditions:

1. The angle of elevation, $\theta_{el,2}$, of each horizon ray from the horizontal should not exceed 12°.
2. The distance from each antenna to its horizon ($d_{Ll,2}$) should not be less than 1/10 or more than 3 times the corresponding smooth earth distance (d_{LS}).

These limitations can be ignored if the values of $d_{L_{1,2}}$, and $\theta_{el,2}$ are entered directly into the program. As is the case with Δh and $h_{gl,2}$ the method of accomplishing this is contained in Appendix B.

Having resolved, or at least indentified, the potential ambiguities in the input parameters, it is useful to briefly describe the output format of the program. As shown in Figs. 4-7, the output of TROPOPLOT consists of two tables containing transmission loss versus distance and signal strength versus distance, a plot of the transmission loss information and a printout of the calculated and input values of many of the program parameters. Some of the quantities in this figure may require some explanation as to their meaning or derivation. These include the variables AE, AES, AED, MS, MD, ADX, DX, K1, K2, and ALS.

--- USER TERRAIN DATA ---

FREQUENCY OF SIGNAL -F- (MEG-HERTZ) 100.00000

DISTANCE (KM)	TRANS-LOSS (DB)	DISTANCE (KM)	TRANS-LOSS (DB)	DISTANCE (KM)	TRANS-LOSS (DB)	DISTANCE (KM)	TRANS-LOSS (DB)	DISTANCE (KM)	TRANS-LOSS (DB)
0.8000	114.41	16.8000	150.25	32.8000	160.75	48.8000	168.12	64.8000	174.50
1.6000	121.11	17.6000	151.09	33.6000	161.16	49.6000	168.46	65.6000	174.80
2.4000	125.19	18.4000	151.90	34.4000	161.56	50.4000	168.79	66.4000	175.10
3.2000	128.21	19.2000	152.70	35.2000	161.95	51.2000	169.13	67.2000	175.40
4.0000	130.65	20.0000	153.32	36.0000	162.34	52.0000	169.46	68.0000	175.70
4.8000	132.71	20.8000	153.86	36.8000	162.73	52.8000	169.78	68.8000	176.00
5.6000	134.52	21.6000	154.38	37.6000	163.11	53.6000	170.11	69.6000	176.30
6.4000	136.15	22.4000	154.89	38.4000	163.49	54.4000	170.44	70.4000	176.59
7.2000	137.63	23.2000	155.39	39.2000	163.87	55.2000	170.76	71.2000	176.89
8.0000	138.99	24.0000	155.88	40.0000	164.24	56.0000	171.08	72.0000	177.18
8.8000	140.27	24.8000	156.36	40.8000	164.61	56.8000	171.40	72.8000	177.47
9.6000	141.47	25.6000	156.84	41.6000	164.97	57.6000	171.72	73.6000	177.76
10.4000	142.61	26.4000	157.30	42.4000	165.33	58.4000	172.03	74.4000	178.05
11.2000	143.69	27.2000	157.75	43.2000	165.69	59.2000	172.34	75.2000	178.34
12.0000	144.73	28.0000	158.20	44.0000	166.05	60.0000	172.66	76.0000	178.63
12.8000	145.73	28.8000	158.64	44.8000	166.40	60.8000	172.97	76.8000	178.91
13.6000	146.69	29.6000	159.08	45.6000	166.75	61.6000	173.28	77.6000	179.20
14.4000	147.62	30.4000	159.50	46.4000	167.09	62.4000	173.59	78.4000	179.49
15.2000	148.52	31.2000	159.93	47.2000	167.44	63.2000	173.89	79.2000	179.77
16.0000	149.40	32.0000	160.34	48.0000	167.78	64.0000	174.20	80.0000	180.05

Figure 4

Sample TROPOPLOT Output

--- SIGNAL STRENGTH VERSUS DISTANCE FOR GIVEN SYSTEM PARAMETERS ---

DISTANCE (KM)	SIG-STRENGTH (DBM)	DISTANCE (KM)	SIG-STRENGTH (DBM)	DISTANCE (KM)	SIG-STRENGTH (DBM)	DISTANCE (KM)	SIG-STRENGTH (DBM)	DISTANCE (KM)	SIG-STRENGTH (DBM)
0.8000----	-48.41	16.8000----	-84.25	32.8000----	-94.75	48.8000----	-102.12	64.8000----	-108.50
1.6000----	-55.11	17.6000----	-85.09	33.6000----	-95.16	49.6000----	-102.46	65.6000----	-108.80
2.4000----	-59.19	18.4000----	-85.90	34.4000----	-95.56	50.4000----	-102.79	66.4000----	-109.10
3.2000----	-62.21	19.2000----	-86.70	35.2000----	-95.95	51.2000----	-103.13	67.2000----	-109.40
4.0000----	-64.65	20.0000----	-87.32	36.0000----	-96.34	52.0000----	-103.46	68.0000----	-109.70
4.8000----	-66.71	20.8000----	-87.86	36.8000----	-96.73	52.8000----	-103.78	68.8000----	-110.00
5.6000----	-68.52	21.6000----	-88.38	37.6000----	-97.11	53.6000----	-104.11	69.6000----	-110.30
6.4000----	-70.15	22.4000----	-88.89	38.4000----	-97.49	54.4000----	-104.44	70.4000----	-110.59
7.2000----	-71.63	23.2000----	-89.39	39.2000----	-97.87	55.2000----	-104.76	71.2000----	-110.89
8.0000----	-72.99	24.0000----	-89.88	40.0000----	-98.24	56.0000----	-105.08	72.0000----	-111.18
8.8000----	-74.27	24.8000----	-90.36	40.8000----	-98.61	56.8000----	-105.40	72.8000----	-111.47
9.6000----	-75.47	25.6000----	-90.84	41.6000----	-98.97	57.6000----	-105.72	73.6000----	-111.76
10.4000----	-76.61	26.4000----	-91.30	42.4000----	-99.33	58.4000----	-106.03	74.4000----	-112.05
11.2000----	-77.69	27.2000----	-91.75	43.2000----	-99.69	59.2000----	-106.34	75.2000----	-112.34
12.0000----	-78.73	28.0000----	-92.20	44.0000----	-100.05	60.0000----	-106.66	76.0000----	-112.63
12.8000----	-79.73	28.8000----	-92.64	44.8000----	-100.40	60.8000----	-106.97	76.8000----	-112.91
13.6000----	-80.69	29.6000----	-93.08	45.6000----	-100.75	61.6000----	-107.28	77.6000----	-113.20
14.4000----	-81.62	30.4000----	-93.50	46.4000----	-101.09	62.4000----	-107.59	78.4000----	-113.49
15.2000----	-82.52	31.2000----	-93.93	47.2000----	-101.44	63.2000----	-107.89	79.2000----	-113.77
16.0000----	-83.40	32.0000----	-94.34	48.0000----	-101.78	64.0000----	-108.20	80.0000----	-114.05

***** FOR A RECEIVER INPUT LEVEL OF -90.00 DBM. DISTANCE BETWEEN ANTENNAS CAN BE AT LEAST 24.00 KM *****

Figure 5

Sample TROPOPLOT Output



Figure 6

Sample TROPOPLOT Output

--- PROGRAM PARAMETERS ---

POLARIZATION (POL)	VERTICAL	
FREQUENCY OF SIGNAL (F)	100.00	MEG-HERTZ
SURFACE CONDUCT)V)TY (S)	0.01500	MHO/METER
SURFACE REFRACT)VITY)NS)	321.00	N-UN)TS
SUM OF ELEVATION ANGLES)TE)	0.00065	RADIANS
D)STANCE BETWEEN ANTENNAS)D)ST)	80.00	K-METERS
ATTENUATION BELOW FREE SPACE)AE)	43.57	DB
)NTEROECILE RANGE OF TERRA)N HEIGHT (DH)	580.00	METERS
SUM OF SMOOTH-EARTH HORIZON DISTANCES (DLS)	19.44	K-METERS
DIFFRACTION ATTENUAT)ON AT D)STANCE DLS)ALS)	54.71	DB
PERMITTIV)TY OR RELATIVE D)ELECTRIC CONSTANT)E)	20.00	
EST)MATED SCATTER ATTENUAT)ON BELOW FREE SPACE (AES)	95.45	DB
STRUCTURAL RECE)VER ANTENNA HEIGHT ABOVE GROUND)H2G)	3.00	METERS
STRUCTURAL TRANSMITTER ANTENNA HEIGHT ABOVE GROUND)H1G)	4.00	METERS
ESTIMATED D)FFRACT)ON ATTENUATION BELOW FREE SPACE)AED)	49.55	DB
COEFFIC)ENT THAT DEFINES SLOPE OF A SMOOTH CURVE OF ACR)K1)	-0.51568	DB/KM
COEFFICIENT THAT DEFINES SLOPE OF A SMOOTH CURVE OF ACR)K2)	-0.86623	DB/KM
SLOPE OF THE CURVE OF SCATTER ATTENUATION AS VERSUS DISTANCE)MS)	-0.04735	DB/KM
D)STANCE WHERE D)FFRACT)ON AND SCATTER ATTENUATIONS ARE EQUAL)DX)	230.35	K-METERS
ATTENUATION WHERE DIFFRACT)ON AND SCATTER ATTENUATION ARE EQUAL)ADX)	106.35	DB
SLOPE OF THE CURVE OF DIFFRACTION ATTENUATION AS VERSUS DISTANCE (MD)	-0.24484	DB/KM

--- SIGNAL STRENGTH DATA)NPUT ---

TRANSM)TTER POWER OUT	100.00	WATTS
TRANSMITTER TRANSMISSION L)NE LOSS	2.00	DB
TRANSMITTER ANTENNA GAIN	10.00	DB
RECEIVER SENS)T)V)TY	-90.00	DBM
RECEIVER TRANSM)SSION L)NE LOSS	2.00	DB
RECEIVER ANTENNA GAIN	10.00	DB

Figure 7

Sample TROPOPLOT Output

In the process of describing these parameters a brief outline of how TROPOPLOT determines path loss is presented. A more detailed exposition can be found in Ref. 6. The median reference value of attenuation below free space, A_{cr}, is computed first. The reference value of transmission loss, L_{cr}, then becomes the sum of the free space attenuation, L_{bf}, and the reference attenuation, A_{cr},

$$L_{cr} = L_{bf} + A_{cr} \text{ dB.}$$

where the free space loss is defined as,

$$L_{bf} = 32.45 + 20 \log_{10} (f \text{ in MHz}) + 20 \log_{10}(d \text{ in km}).$$

The reference attenuation, A_{cr}, is determined using one of three subroutines depending on the particular mechanism of propagation; LOS for line of sight modes, DIFF for diffraction, and SCATT for tropo-scatter. Two ray optics is used to compute line of sight paths while diffraction paths are assumed to be over a double knife edge and a value of diffraction attenuation below free space, A_d, is computed. In the case of scattering the attenuation variable is designated as A_s. The reference attenuation A_{cr} is determined by the smaller value of A_d and A_s. In the line of sight case the attenuation is calculated for 2 values of distance (d_0,d_1) for which line of sight propagation is valid to produce corresponding values of attenuation A_0 and A_1. The diffraction attenuation, A_{Ls}, is computed at the distance

d_{Ls} and together with A_o and A_1 is used to determine the slopes, k_1 and k_2, of a smooth curve of the reference attenuation versus distance over the range $1 \leq d \leq d_{Ls}$

$$A_{cr} = A_o + k_1(d-d_o) + k_2 \log_{10}(d/d_o) \text{ dB.}$$

The output parameter A_e is defined as

$$A_e = A_o - k_1 d_o - k_2 \log_{10} d_o \quad \text{(i.e., d=1)}$$

so for $1 \leq d \leq d_{LS}$

$$A_{cr} = A_e + k_1 d + k_2 \log_{10} d$$

When the diffraction attenuation is computed the output variables A_{ed} and m_d come into consideration. The diffraction attenuation is computed as the weighted average of the diffraction attenuation over smooth earth, A_r, and the attenuation over a double knife edge surface, A_k, where

$$A_d = (1-w)A_k + wA_r \text{ dB}$$

A description of the method of weighting these estimators and calculating A_d and A_k is contained in Annex 3 to Ref. 6. The diffraction attenuation, A_d, is determined at two distances, d_3 and d_4, in the far diffraction region, and a straight line through the points (A_3,d_3) and (A_4,d_4) is defined as

$$m_d = (A_4 - A_3)/(d_4 - d_3) \text{ dB/km} \quad \text{(slope)}$$

and

$$A_{ed} = A_{fo} + A_4 - m_d d_4 \qquad \text{(intercept)}$$

where A_{fo} is a "clutter factor" ($\leq$ 15 dB).

If the scatter attenuation is less than the diffraction attenuation, as is sometimes the case in trans-horizon paths where the distance d or the angular distance θ is large, then $A_{cr} = A_s$. When the product of d in kilometers and θ in radians is greater than 0.5, A_s is computed at large distances, d_5 and d_6, and a straight line through the points (A_5,d_5) and (A_6,d_6) is defined as follows:

$$m_s = (A_6 - A_5)/(d_6 - d_5)$$

and

$$A_{es} = A_5 - m_5 d_5.$$

As before the reference attenuation then becomes

$$A_{cr} = A_s = A_{es} + m_s d \qquad d \geq d_x$$

The quantity d_x is defined as the distance where the scatter attenuation is equal to the diffraction attenuation.

It can be seen from the above description and Ref. 6 that the actual determination of the output quantities is somewhat complex and for most applications the information contained in the graphs and tables describing path loss and signal strength is sufficient. Consequently the data presented in the next sub-section will primarily consist of derivations from those portions of the output. If the quantities in

Fig. 6 are important to the user it should be noted that for certain input combinations the format statements contained in the TROPOPLOT program will produce an all asterisk, "*******", printout indicating that the format statement governing that particular variable requires modification.

B. ACTUAL PATH LOSS MEASUREMENTS

1. Procedure

In order to obtain the proper input parameters for entry into TROPOPLOT certain preliminary measurements and calculations were required. The first step was to obtain charts of the path area[1] and from these determine the terrain profile over a great circle path between transmitter and receiver. The great circle path was approximated by a rhumb line for path lengths less than 70 kilometers and the availability of 7½' topographic charts for the longer paths enabled the use of straight lines over the chart area. This profile information was plotted on a curved earth's surface using the plotting program described in Appendix A. The value of the surface refractivity used in determining the effective earth's radius was the same as that used in the input to the

---

[1] To obtain a catalogue for U.S. Charts write to

Denver Distribution Section
U.S. Geological Survey
Denver Federal Center, Building 41
Denver, Colorado 80255

program and can readily be obtained from Ref. 9 or from actual meteorological data. If the charts of Bean et al. (1960) are used this value must be converted from N_o to N_s by the equation

$$N_s = N_o \exp(-0.1057\ h_s)$$

The value of h_s used depends on several factors most important of which is the mode of propagation. For most of the paths considered herein the value of h_s chosen was determined by the elevation of the lowest antenna. For trans-horizon paths a mean N_s is computed using heights at the obstacle horizons. As was previously noted the values of N_s for input can range from 250 to 400 N-units, so it is obvious that predictions of path loss for anomalous conditions are not readily obtained using TROPOPLOT which is designed for long-term and median input parameters. The effects of non-standard atmospheric conditions along these paths are considered in Section III.

After plotting the path profile the required input parameters were determined using the methods described in Appendix B and a number of parameters were varied to produce the results described below.

2. Results

The output of the path profile/routine for each path considered is shown in Figs. 8-19 while the corresponding input parameters used are contained in Table I. All the links were analyzed for path loss at both VHF and S-band to



Figure 8

Terrain Profile for the Zelatched Point to Keyport Path



Figure 9

Terrain Profile for the Makah to Striped Peak Path



Figure 10

Terrain Profile for the Lookout Mt. to Keyport Path



Figure 11

Terrain Profile for the Zelatched Point to Bangor Path



Figure 12

Terrain Profile for the Mt. Constitution to Gold Mt. Path



Figure 13

Terrain Profile for the Striped Peak to
Mt. Constitution Path



Figure 14

Terrain Profile for the Bangor to Gold Mt. Path



Figure 15

Terrain Profile for the Keyport to Gold Mt. Path



Figure 16

Terrain Profile for the Lookout Mt. to NOEF, Bangor Path



Figure 17

Terrain Profile for the NOEF, Bangor to Gold Mt. Path



Figure 18

Terrain Profile for the Zelatched Point to NOEF, Bangor Path



Figure 19

Terrain Profile for the Lookout Mt. to Bangor Path

illustrate the increase in path loss when frequency is increased. The results are shown in Figs. 20-31. The quantities (referred to in an above sub-section) which required interpretation as to the precise value to be used in detailed terrain studies are varied for a single path so that the effects of this variation can be shown. A sample path (Lookout Mt. to Keyport) was selected for this purpose and the effects of several different antenna heights in an unmodified version of TROPOPLOT are shown in Fig. 32. These same antenna heights are then entered into the modified program and the results shown in Fig. 33. To show the effects of variations in conductivity and permittivity σ and ε are varied over the same path with the results shown in Fig. 34. The effect of variations in the value of Δh is shown in Fig. 35. The quantity $\Delta\bar{h}$ was computed by taking the mean value of Δh over all the paths considered, Δh_t is the tabulated estimation of terrain irregularity found in both Ref. 6 and Ref. 7, Δh_r is the parameter computed by the methods of Appendix B. This comparison is intended to show the degree of precision required in choosing a parameter when uncertainty over the means of selection is present.

The importance of detailed path profile information is pointed up in the Zelatched Pt. to Keyport path (Fig. 8). If TROPOPLOT is used without modification, errors in prediction can occur at 2000 MHz the results of which are shown in Fig. 20. Note that this output predicts free space attenuation,



Figure 20

Transmission Loss vs. Distance for the Zelatched Pt. to Keyport Path



Figure 21

Transmission Loss vs. Distance for the Makah to Striped Peak Path



Figure 22

Transmission Loss vs. Distance for the Lookout Mt. to Keyport Path



Figure 23

Transmission Loss vs. Distance for the Zelatched Point to Bangor Path



Figure 24

Transmission Loss vs. Distance for the Mt. Constitution to Gold Mt. Path



Figure 25

Transmission Loss vs. Distance for the Striped Peak to Mt. Constitution Path



Figure 26

Transmission Loss vs. Distance for the Bangor to Gold Mt. Path



Figure 27

Transmission Loss vs. Distance for the Keyport to Gold Mt. Path



Figure 28

Transmission Loss vs. Distance for the Lookout Mt. to NOEF, Bangor Path



Figure 29

Transmission Loss vs. Distance for the NOEF,
Bangor to Gold Mt. Path



Figure 30

Transmission Loss vs. Distance for the Zelatched Point to NOEF, Bangor Path



Figure 31

Transmission Loss vs. Distance the Lookout Mt. to Bangor Path



Figure 32

Antenna Height Variation for an Unmodified Version of TROPOPLOT
Transmission Loss vs. Distance



Figure 33

Antenna Height Variation for the Modified Version of TROPOPLOT
Transmission Loss vs. Distance



Figure 34

Variation in ε and σ for the Lookout to Keyport Path
Transmission Loss vs. Distance



Figure 35

Variation in Δh for the Lookout Mt. to Keyport Path
Transmission Loss vs. Distance

when there is clearly a large attenuation of the signal by path obstacles. The same error can occur when the modified program is used; primarily due to the fact that the terrain is represented statistically. Large deviations from the range of terrain heights occurring in mid-path may not be considered as an obstacle by the program when in fact it is a major factor in the attenuation process. These smoothing effects can be alleviated somewhat by examining the terrain profile and performing graphical analysis, such as is described in Refs. 1-5, to check the effectiveness of the computer routine when its output is questionable. Another possible source of error can occur in short paths where only a single knife edge obstacle is present. In this case the predicted value of path loss is too high since a non-LOS path loss is calculated for a double knife edge case.

3. Conclusions

It is obvious that the quality of the output of this tropospheric propagation prediction program depends on which of several possible assumptions were made concerning the choice of input parameters. Clearly, if information is desired concerning a particular path or path area a path profile should be drawn and the ray path checked to insure that the values of the corresponding angles of elevation (depression) fall within the program constraints. As previously stated, if these values exceed the limits then TROPOPLOT must be modified and a detailed terrain profile obtained.

The effect of the variations of several of the parameters shown above allow some inferences to be drawn concerning the care with which the input variables must be chosen. It would seem from the path studied that variations of σ and ε have the least effect on path loss (<1 db), variations in Δh have only a small effect, particularly for longer distances, and variations in antenna height have the greatest effect on path loss. The unmodified version of the program appears more susceptible to these changes than the version modified to accept detailed profile information. The sensitivity of the transmission loss to antenna height value variation was alluded to in an earlier section and thus the suggestion that care be exercised in selecting these values is well taken if any degree of precision is desired. The detailed computation of Δh, on the other hand, is not necessary. By using the tabulated values corresponding to a particular type of terrain [Ref. 6] similar results can be obtained.

The transmission loss predictions seem to be accurate, or at least within an expected range of values except for short diffraction paths. In order to assess the goodness of the prediction, comparison with empirical data for these paths should be accomplished in a later study.

III. PROPAGATION IN A NON-STANDARD ATMOSPHERE

The computer analysis conducted in the previous section produced a long-term median attenuation value as output and consequently required that standard atmospheric conditions be assumed. In providing input under this assumption, the "standard" atmosphere for the locations under consideration was characterized by the median value of minimum monthly surface refractivity at sea level (N_o) corrected to emitter elevation. This element of the prediction routine could, in some cases, lead to an over-optimistic expectation of link performance, particularly in a locale where anomalous conditions frequently occur. One method of avoiding this potential source of error is to examine the statistical occurrence of these conditions and the severities of the effect of the anomalies on the link in question. For the purposes of this study the non-standard conditions dealt with involved the super-refractive, subrefractive and ducting cases. The statistics used in this determination were derived from IREPS output and the effects of non-standard refractivity were modeled by assuming certain values of effective earth's radius for corresponding conditions. Prior to the presentation of these results the theory involved in the anomalous propagation problem is reviewed.

A. THEORY

The primary medium through which electro-magnetic waves with wavelengths less than 1 or 2 meters propagate is the troposphere. This region, bounded below by the earth's surface and above by the tropopause, is approximately 10 km thick and is characterized by a general decrease in temperature with height up to a zone of constant temperature called the tropopause. The tropopause is not a static boundary, but has a height which is variable with both time and latitude.

The troposphere is usually assumed to be a lossless dielectric with $\mu = 1$ and $\sigma = 0$. The index of refraction, n, is then

$$n = \sqrt{\varepsilon}_{r\ atm.}$$

At the earth's surface n has been found to equal approximately 1.0003. Since air with a higher water vapor content has a larger value of permittivity, that is,

$$\varepsilon_{wet\ air} \geq \varepsilon_{dry\ air}$$

and since the lower atmosphere usually has the higher water vapor content, the permittivity of the atmosphere exhibits a decrease with height to a value of unity. This effect causes the refractive index to similarly decrease with height. It has been ascertained [Ref. 3] that for temperate climates the average variation near the ground is

$$\frac{dn}{dh} = -\ 0.039 \times 10^{-6}\ \text{per meter}$$

In order to avoid the use of such small numerical quantities a variable, N, designated as the refractivity or co-index of refraction, has been defined as

$$N = (n-1)\times 10^6 \quad \text{N-units}$$

and so within one kilometer of the earth's surface

$$\frac{dN}{dh} = -39 \text{ N-units/meter}$$

A standard atmosphere is then defined in Refs. 11 and 12 as follows:

1. $\varepsilon = 1$;
   $n = 1$

2. $\frac{dT}{dh} = \frac{1}{150} \frac{°C}{m}$

3. $N = \frac{77.6}{T}\left(p + 4810 \frac{e}{T}\right)$

   p = pressure (mb)
   T = absolute temp. (°K)
   e = vapor pressure (mb)

By assuming a linear refractivity gradient it is possible to define an effective earth radius as was done in an earlier part of this report. This allows the rays representing the radio wave to be drawn as straight lines over a curved earth. An alternative representation which enables the effect of several different values of effective earth radius to be shown on the same profile is to show the rays as curves from transmitter to receiver over a plane earth. Details of constructing this sort of representation are presented in Refs. 3 and 13.

Non-standard propagation can occur when the above conditions are not met. This is manifested by the manner in which the radio wave path is curved. Under normal conditions the decrease of the refractive index with height causes a downward bending of the wave path. Changes in the refractive index super-refraction or in certain cases an upward bending of the ray which is termed subrefraction. If the refractive effects are severe enough, the formation of ducts occurs in which the majority of radio wave energy is trapped within a narrow region.

Ducting can occur as a result of a number of different atmospheric conditions. The primary requirement in producing this phenomena is that the curvature of the radio wave must be greater than that of the earth. This is produced by a rapid change in N with height which is caused by a sharp decrease in moisture with height (abnormal moisture lapse rate) and/or a sharp increase in temperature with height (temperature inversion). The formation of a ground- or surface-based duct can occur when warm dry air flows from land over water. Moisture evaporates from the water into the lower layers of air cooling the air and producing an increased moisture lapse rate and a temperature inversion. The downward motion of warm dry air is frequently associated with the clear weather found on the eastern side of vast high pressure regions in the lower and middle atmosphere. Subsidence such as this can also result in elevated ducts which are found to be strongest and

lowest in fair weather and highest and weakest near storms. Surface ducts are also formed in certain regions by nocturnal cooling but unlike the evaporation duct this sort of anomaly if found over land, particularly desert regions.

The opposite effect to super-refractive ducting is the upward bending of radio waves caused by an increase in refractivity with height. This condition typically occurs in moist and cloudy regions.

The determining factor in all the above cases is the refractivity gradient. Table II below, found in Ref. 11, shows the range of refractivity gradients over which anomalous conditions prevail.

Table II. Range of refractive index gradient for differing types of propagation conditions.

P (mb)	h (km)	Sub-Refractive	Unstratified	Super-Refractive
1000-850	0-1.46	$-dn/dh \leq 0$	$20 \leq -dn/dh \leq 60$	$100 \leq -dn/dh$
850-700	1.46-3.01	$-dn/dh \leq 0$	$20 \leq -dn/dh \leq 50$	$80 \leq -dn/dh$
700-600	3.01-4.20	$-dh/dh \leq 0$	$20 \leq -dn/dh \leq 40$	$70 \leq -dn/dh$
600-500	4.20-5.57	$-dh/dh \leq 0$	$20 \leq -dn/dh \leq 30$	$50 \leq -dn/dh$
500-400	5.57-7.18	$-dn/dh \leq 0$	$20 \leq -dn/dh \leq 25$	$40 \leq -dn/dh$

The refractivity gradient can be related to the effective earth radius and the resulting ray trace when drawn on the terrain profile corresponding to this radius, will show the effect of the anomaly on a particular path.

The following holds for most conditions [Ref. 3]:

$$\text{effective radius} = k = \frac{1}{1+6.4\times10^{-3}\,dN/dh}$$

From this relationship it can be seen that for the standard refractivity gradient, which was defined as -39 N-units/km, the effective earth radius would be equal to 4/3. The presence of anomalous conditions thus cause an effective earth radius greater or less than 4/3. The interrelationship of the refractivity gradient, the radius of curvature of the wavefront, the effective radius, and the assoicated types of refraction are shown in Table III [Ref. 3].

Note that there is some difference in the exact gradient value which defines super-refraction. The super-refractivity gradient referred to in Table II includes both the extended range and the ducting conditions, while that referred to in Table III includes only the ducting case.

In the actual paths under study several values of effective earth radius were used to simulate the effect of anomalous conditions. Table IV [Ref. 15] provides a guide to the use of k as an estimate of propagation conditions for 99.9%-99.99% path reliability.

Table III. Relationship of Refractive Gradient to Various Propagation Variables.

$\frac{dN}{dh}$ $\frac{\text{N-units}}{\text{km}}$	Curvature	ρ (in km)	K	Atmospheric Refraction	Virtual Earth	Horizontally Launched Ray
> 0	Upward		< 1	Below Normal	More Convex than Actual	Moves Away from earth
$= 0$	Nil	∞	1		Actual Earth	
$0 > \frac{dN}{dh} > -39$	Down		> 1		Less Convex than Actual Earth	
-39		25,600	4/3	Normal		
$-39 > \frac{dN}{dh} > -157$			$>4/3$	Above Normal		
-157		a=6350 = ρ	∞		Plane	Remains Parallel to Earth
< -157			< 0	Super-refractive	Concave	Draws Closer to Earth

Table IV. K Factor Guide.

	Propagation Conditions				
	Perfect	Ideal	Average	Difficult	Bad
Weather	Standard atmosphere	No surface layer or fog	Substandard light fog	Surface layers, ground fog	Fog moisture over water
Typical	Temperate zone, no fog, no ducting, good atmospheric mix day and night	Dry, mountainous, no fog	Flat, temperate, some fog	Coastal	Coastal, water, tropical
K Factor	1.33	1-1.33	0.66-1.0	0.66-0.5	0.5-0.4

The path profiles from Keyport to Gold Mt., Keyport to Lookout Mt., and Bangor to Lookout Mt. are shown for two values of K; 0.5 which represents the difficult case as either when one antenna is inside a duct and the other outside, or the subrefractive condition, and -3.57 which represents a subrefractive gradient of -200 N-units/km. The effect of the change in earth radius shown in Figs. 36-41 is most noticeable in the Keyport to Lookout Mt. path. Using graphical methods of analysis found in Refs. 1 and 3 the approximate degradation in link performance can be estimated. While little change is observed in the Keyport to Gold Mt. link due to the shortness of the path length, the Keyport to Lookout Mt. path with K = ½ exhibits an additional loss of up to 60 db over that found in



Figure 36

Path Profile for Lookout Mt. to Keyport (K=1/2)



Figure 37

Path Profile for Lookout Mt. to Keyport (K=1)



Figure 38

Path Profile for Keyport to Gold Mt. (K=1/2)



Figure 39

Path Profile for Keyport to Gold Mt. (K=1)



Figure 40

Path Profile for Lookout Mt. to Bangor (K=1/2)



Figure 41

Path Profile Lookout Mt. to Bangor (K=1)

standard atmospheric conditions. This same path however suffers no apparent degradation for K = 1 as the Fresnel zone clearance remains greater than .6. The Lookout Mt. to Bangor path degradation was found to be 12-30 db for K = ½ and 6-15 db for K = 1. From these results it can be seen that changes in effective earth radius can have a significant effect on path loss, particularly as the path length increases

The profile representation using N data is the most commonly used in the literature, however the depiction of ducting or trapping types of profiles is often done with modified or M-unit profiles where

$$M = N + \frac{(a)}{h} \times 10^6$$

a = actual earth radius

h = height above sea level

This adjustment to the N-profile is used in the anomalous case since straight rays above a curved earth now become curved rays above a planar earth and the duct can be more clearly shown. The variability of M curves corresponding to a particular propagation condition is shown in Table V which was derived from Ref. 16.

The M-curve is thus a transformation in which the relative curvature between the normal of the electro-magnetic wavefront and the surface of the earth is unchanged. A duct is formed whenever the M curve has a relative minimum. The base of an elevated duct is the height on the M curve below the minimum that has the same M value as the relative minimum.

When no such height exists, the base of the duct is at the ground and a so-called ground based duct exists [Ref. 12]. The main disadvantage in the use of M data is that above the duct N is grossly overcorrected.

Table V. Variability of M curves with type of transmission conditions.

M	M-Curve	Type of Transmission
Increases linearly	Straight line, with positive slope	Standard
	Slope decreases near earth surface with rays curving up	Substandard
	Slope increases near surface with less upward curve	Superstandard
	Vertical, no curve	Very great coverage
Decreases with height	Slope linear and negative rays curve down	Trapping or ducting

Having demonstrated the effect of anomalous conditions on several propagation paths and considered the theory involved the next step is to determine the frequency with which these conditions occur. The method chosen to accomplish this was to access the IREPS historical file for the geographical area in question as described in the following section.

B. INTEGRATED REFRACTIVE EFFECTS PREDICTION SYSTEM (IREPS)[2]

IREPS is an experimental system ultimately designed to provide the capability for on-board assessment of the effect of atmospheric anomalies on sensor performance. The hardware portion of the system consists of a mini-computer with an interactive graphics terminal on which the required inputs are entered and the results displayed in an easily understood graphic format. The information stored in the systems memory includes a refractivity library containing long-term meteorological statistics on the occurrence of ducting conditions as a function of location. This library data is obtained from radiosonde stations throughout the world and can be augmented by on-scene refractometer or radiosonde data input in order to tailor the output to a particular location. In the case of the Washington paths, there were only two upper air sounding stations in the vicinity of the sites. One is located at Tatoosh Island (48°-24'N, 124°-42'W) and the other at Quillayute (48°-00'N, 124°-36'W). The historical propagation summaries for each location are shown in Figs. 42 and 43. Note that while the statistics generated are geared toward radar performance, the frequencies to be used in the link are included so that some information concerning potential anomalies can be derived. The historical meteorological data for each station, shown in Figs. 44 and 45, provides information concerning median conditions in the vicinity of the

---

[2]For a detailed description of the system see Ref. 10.

sounding station and shows the seasonal and diurnal variation in this data. Based on this data, the program then can generate a series of profiles. Figures 46 and 47 are M and N profiles in the vicinity of the two sounding stations. Also available in the program output capabilities is a ray trace diagram from a particular emitter. This is useful in a qualitative sense in that it shows potential areas of non-coverage which may be important in maintaining a ground to air communications link. The first set of traces demonstrates the effect on the ray trace diagram of selected sites for the median ducts found in the Tatoosh Island profile and are shown in Figs. 48-52. A second set of traces are shown in Figs. 54-57 exhibiting the effect of an elevated duct between 1100 and 1400 feet. The profile responsible for this condition is shown in Fig. 53. The third set of traces show a duct between 2300 and 2900 feet in Figs. 59 and 60 and the corresponding profile in Fig. 58.

Besides the above mentioned output format the IREPS program can also provide path loss information, with a detection threshold for a particular sensor superimposed on the distance vs. dB display and also a coverage diagram for a particular sensor. These two output diagrams were not produced for this study but an example of each is included in Figs. 61 and 62 [Ref. 10].

HISTORICAL PROPAGATION CONDITION SUMMARY

```
LOCATION:   48 24 N     124 36 W
SEASON:     ALLYEAR
TIME   :    DAY & NIGHT

SURFACE TO SURFACE:

    6 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES 30 MHZ TO  1 GHZ
    6 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES  1 GHZ TO  3 GHZ
    7 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES  3 GHZ TO  6 GHZ
   19 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES  6 GHZ TO 10 GHZ
   42 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES ABOVE     10 GHZ

SURFACE TO AIR:

    2 % PROBABILITY FOR:
    EXTENDED RANGES UP TO MEDIAN ALTITUDE OF     92. METERS
    POSSIBLE HOLES ABOVE  MEDIAN ALTITUDE OF     92. METERS

AIR TO AIR:

    4 % PROBABILITY FOR:
    EXTENDED RANGES FOR MEDIAN ALTITUDES BETWEEN   735. AND   816. METERS
    POSSIBLE HOLES  FOR MEDIAN ALTITUDES ABOVE     816. METERS

GENERATE PROFILE (STANDARD,ELEVATED,SURFACE,ALL,NONE)?
```

Figure 42

Historical Propagation Conditions for Tatoosh Island, Wash.

HISTORICAL PROPAGATION CONDITION SUMMARY

```
LOCATION    48 00 N     124 36 W
SEASON      ALLYEAR
TIME        DAY & NIGHT

SURFACE TO SURFACE:

   11 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES 30 MHZ TO  1 GHZ
   12 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES  1 GHZ TO  3 GHZ
   13 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES  3 GHZ TO  6 GHZ
   25 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES  6 GHZ TO 10 GHZ
   47 % PROBABILITY OF EXTENDED RANGES FOR FREQUENCIES ABOVE    10 GHZ

SURFACE TO AIR:

    8 % PROBABILITY FOR:
    EXTENDED RANGES UP TO MEDIAN ALTITUDE OF    68. METERS
    POSSIBLE HOLES ABOVE  MEDIAN ALTITUDE OF    68. METERS

AIR TO AIR:

   15 % PROBABILITY FOR:
    EXTENDED RANGES FOR MEDIAN ALTITUDES BETWEEN  1090. AND  1187. METERS
    POSSIBLE HOLES  FOR MEDIAN ALTITUDES ABOVE    1187. METERS

GENERATE PROFILE (STANDARD,ELEVATED,SURFACE,ALL,NONE)?
```

Figure 43

Historical Propagation Conditions for Quillayute, Wash.

HISTORICAL METEOROLOGICAL DATA FOR LOCATION: 48 24 N 124 36 W
TIME: ALLYEAR DAY & NIGHT

UPPER AIR PROFIL SOURCE: TATOSH WASH,USA 48 24 N 124 42 W
EVAPORATION DUCT SOURCE: MARSDEN SQ 159 45 0 N 145 0 W

MEDIAN SURFACE N UNITS: 332. MEDIAN N UNIT GRADIENT: -53.0 (N/KM)
MEDIAN SURFACE DUCT: INTENSITY 1. MUNITS, TOP 92.MTRS
MEDIAN ELEVATD DUCT: INTENSITY 2. MUNITS, TOP 816.MTRS, BASE 735.MTRS

	YEARLY AVG	WINTER DAY	WINTER NIGHT	SPRING DAY	SPRING NIGHT	SUMMER DAY	SUMMER NIGHT	AUTUMN DAY	AUTUMN NIGHT
%SURFACE DUCTS	2 2	0.0	0.0	10.3	1.3	5.3	1.0	0.0	0.0
%ELEVATED DUCTS	4 2	0.0	0.0	5.0	14.0	5.3	9.0	0.0	0.0
EVAPORATION DUCTS									
% 0 TO 3 METERS	23.6	26.4	26.1	29.3	27.9	24.4	21.3	16.9	16.7
% 3 TO 6 METERS	22.1	22.0	26.5	23.1	29.4	18.0	23.7	15.5	18.2
% 6 TO 9 METERS	21.9	23.1	25 4	18.9	22.0	17.2	24.5	19.8	24.3
% 9 TO 12 METERS	15.2	16.1	14.2	11.7	12.1	13.7	13.6	20.0	20.0
% 12 TO 15 METERS	7.2	5.7	4.7	5.1	3.6	7.4	7.3	12.4	11.2
% 15 TO 18 METERS	3 2	2.4	1.2	2.2	1.4	4.1	3.0	6.4	5.2
% 18 TO 21 METERS	1 5	1.0	0.6	1.1	0.6	2.2	1.6	2.9	1.9
% 21 TO 24 METERS	0.6	0.1	0.2	0.7	0.2	1.5	0.6	1.0	0.6
% 24 TO 27 METERS	0.5	0.5	0.2	0.6	0.3	0.9	0.6	0.9	0.3
% 27 TO 30 METERS	0 3	0.3	0.0	0.4	0.1	0.6	0.5	0.5	0.2
% > 30 METERS	3.8	2.4	0.8	6.7	2.5	9.9	3.4	3.6	1.4
MEAN DUCT HT MTRS	8 7	7.6	6.4	9.2	6.9	12.0	8.5	10.3	8.7
MEAN WIND SP M/S	7 1	9.3	9.3	6.2	6.2	5.7	5.7	7.2	7.2

GENERATE PROFILE (STANDARD,ELEVATED,SURFACE,ALL,NONE)?

Figure 44

Historical Meteorological Data for Tatoosh Island, Wash.

HISTORICAL METEROLOGICAL DATA FOR LOCATION: 48 00 N 124 36 W
TIME: ALLYEAR DAY & NIGHT

UPPER AIR PROFIL SOURCE: QUILAYUT WASH,USA 48 0 N 124 36 W
EVAPORATION DUCT SOURCE MARSDEN SQ 159 45 0 N 145 0 W

MEDIAN SURFACE N UNITS: 324. MEDIAN N UNIT GRADIENT: -44.0 (N/KM)
MEDIAN SURFACE DUCT: INTENSITY 3. MUNITS, TOP 68.MTRS
MEDIAN ELEVATD DUCT: INTENSITY 3. MUNITS, TOP 1187.MTRS, BASE 1090.MTRS

	YEARLY AVG.	WINTER DAY	WINTER NIGHT	SPRING DAY	SPRING NIGHT	SUMMER DAY	SUMMER NIGHT	AUTUMN DAY	AUTUMN NIGHT
%SURFACE DUCTS	7.6	4.7	4 0	21.3	1.0	18.7	5.0	3.3	2.7
%ELEVATED DUCTS	14.6	5.3	4.7	9.7	23.3	19.7	34.3	6.7	13.0
EVAPORATION DUCTS									
% 0 TO 3 METERS	23.6	26.4	26.1	29.3	27.9	24.4	21.3	16.9	16.7
% 3 TO 6 METERS	22.1	22.0	26.5	23.1	29.4	18.0	23.7	15.5	18.2
% 6 TO 9 METERS	21.9	23.1	25.4	18.9	22.0	17.2	24.5	19.8	24.3
% 9 TO 12 METERS	15.2	16.1	14.2	11.7	12.1	13.7	13.6	20.0	20.0
% 12 TO 15 METERS	7.2	5.7	4.7	5.1	3.6	7.4	7.3	12.4	11.2
% 15 TO 18 METERS	3.2	2.4	1.2	2.2	1.4	4.1	3.0	6.4	5.2
% 18 TO 21 METERS	1 5	1.0	0.6	1.1	0.6	2.2	1.6	2.9	1.9
% 21 TO 24 METERS	0.6	0.1	0.2	0.7	0.2	1.5	0.6	1.0	0.6
% 24 TO 27 METERS	0.5	0.5	0.2	0.6	0.3	0.9	0.6	0.9	0.3
% 27 TO 30 METERS	0.3	0.3	0.0	0.4	0.1	0.6	0.5	0.5	0.2
% > 30 METERS	3.8	2.4	0.8	6.7	2.5	9.9	3.4	3.6	1.4
MEAN DUCT HT MTRS	8.7	7.6	6.4	9.2	6.9	12.0	8.5	10.3	8.7
MEAN WIND SP M/S	7.1	9.3	9.3	6.2	6.2	5.7	5.7	7.2	7.2

GENERATE PROFILE (STANDARD,ELEVATED,SURFACE,ALL,NONE)?

Figure 45

Historical Meteorological Data for Quillayute, Wash.



Figure 46

Median Profiles for Quillayute, Wash.



LOCATION 48 24 N 124 36 W WIND SPEED 7.1 METERS/SEC
TIME ALLYEAR DAY & NIGHT EVAPORATION DUCT HEIGHT 8.7 METERS

(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 47

Median Profiles for Tatoosh Island



LOCATION: 48 24 N 124 36 W
TIME: ALLYEAR DAY & NIGHT
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 48

Winchelsea Island Ray Trace for Median Conditions



LOCATION: 48 24 N 124 36 W
TIME: ALLYEAR DAY & NIGHT
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 49

Lookout Mt. Ray Trace for Median Conditions



LOCATION: 48 24 N 124 36 W
TIME: ALLYEAR DAY & NIGHT
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 50

Makah Ray Trace for Median Conditions



LOCATION: 48 24 N 124 36 W
TIME: ALLYEAR DAY & NIGHT
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 51

Striped Peak Ray Trace for Median Conditions



LOCATION: 48 24 N 124 36 W
TIME: ALLYEAR DAY & NIGHT
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 52

Mt. Constitution Ray Trace for Median Conditions



LOCATION NOT SPECIFIED
TIME NOT SPECIFIED

WIND SPEED 0.0 METERS/SEC

(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 53

Profiles Required to Produce an Elevated Duct Between 1100-1400 Feet



LOCATION: NOT SPECIFIED
TIME: NOT SPECIFIED
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 54

Ray Trace from Mt. Constitution for an Elevated Duct



LOCATION: NOT SPECIFIED
TIME: NOT SPECIFIED
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 55

Ray Trace from Striped Peak for an Elevated Duct



LOCATION: NOT SPECIFIED
TIME: NOT SPECIFIED
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 56

Ray Trace from Makah for an Elevated Duct



LOCATION: NOT SPECIFIED
TIME: NOT SPECIFIED
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 57

Ray Trace from Lookout Mt. for an Elevated Duct



LOCATION NOT SPECIFIED
TIME NOT SPECIFIED

WIND SPEED 0.0 METERS/SEC

(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 58

Profiles Required to Produce an Elevated Duct Between 2300-2900 Feet



LOCATION: NOT SPECIFIED
TIME: NOT SPECIFIED
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 59

Ray Trace from Lookout Mt. for an Elevated Duct



LOCATION: NOT SPECIFIED
TIME: NOT SPECIFIED
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 60

Ray Trace from Mt. Constitution for an Elevated Duct



LOCATION: NOT SPECIFIED
TIME: NOT SPECIFIED
(PLOT,EDIT,LIST,SUMRY,RAYS,LOSS,COVER,END)?

Figure 60

Ray Trace from Mt. Constitution for an Elevated Duct



Figure 61

Coverage Diagram (IREPS)



Figure 62

Path Loss Display (IREPS)

This system is not yet operational and is still undergoing testing. The value of the output formats in evaluating link anomalous propagation potential is clearly obvious. If data were available for each of the sites analyzed in the study a more exact picture of the statistics of propagation would be available.

Based on the available data for the Washington area several inferences can be made concerning anomalous propagation. For the frequencies in question the probability of extended ranges or ducting is between 8 and 10 percent while no statistics are presented for below normal refraction. For the locations from which the soundings are available it can be seen that surface ducting occurs most often in the daytime during Spring and that the ducts are predominantly less than 12 meters in thickness. The lowest occurrence of surface ducts at Quillayute is in the spring night which also has the highest incidence of elevated ducts. At Tatoosh which is a more classically marine climate, there are no ducts observed to occur during the autumn and winter either at night or during the day. The differences in the median refractivity at sea level are not significant and both values, 332 for Tatoosh and 324 for Quillayute, would produce an effective earth radius greater than 4/3, and consequently better than average propagation conditions prevail. Until meteorological data is available for the actual sites the ray trace diagrams

can provide only an indication of the effect of a certain profile on the emitter in question rather than actual information concerning real conditions present in the link components.

APPENDIX A

Path Plotting Program

In order to plot a path profile on a curved earth surface either commercially available profile paper must be used or the profile can be manually or computer generated. Instructions for the construction of path profile paper for various values of earth radius can be found in Ref. 13. Computer generated profiles can be easily produced if a plotting package is available. For the purposes of this study a subroutine known as DRAWP was locally available. Other alternative plotting methods included the TEKTRONIX 4012 and HP 9830 plotting packages, both of which are available at the Naval Postgraduate School.

The program used made use of a transformation which allowed the terrain profile to be plotted on a linear graph by adjusting the height at a particular distance for the effective curvature of the earth. The profile is drawn by the CALCOMP plotter along with the earth surface at sea level. The program also fits a line to the terrain data by the method of least squares and forms the difference between the value of height found on the line and the actual value of the terrain height at the same distance. Aside from the actual terrain data points the only input parameters necessary to obtain this output are either the refractivity gradient or the surface refractivity, and the number of points input.

The output provided by the program includes a plot of the terrain on the effective earth surface, a table of height vs. input distance, a list of the terrain heights in kilometers, the effective earth radius, and the difference between each point on a least square curve and the actual terrain data points without the correction for earth curvature applied. In order to perform the curve to fit terrain referred to in Appendix B, a new set of points must be used taking only those the points visible to both transmitter and receiver instead of the entire terrain profile.

The format of the input data deck is presented below:

First Data Card:

Column 1: Code "1". surface refractivity will be used as input

Code "2". refractivity gradient will be used as input

Second Data Card:

Column 1-10: Number of data points (right justified integer $\leq$ 200)

Column 10-20: Refractivity or gradient (right justified integer)

Third Through Last Data Card:

The distance points in kilometers are listed in order using real numbers (i.e., F10.5 format) in columns 1-10, 11-20, ..., 61-70. The heights above sea level in feet follow directly after the distance listing in the same format. A new card is not started unless the last distance point was listed in Columns 61-70

An example of the latter cards is shown below

For the table of distance vs. height below

Distance (km)	Height (feet)
0.0	420.
1.0	500.
2.0	10.
3.0	125.5
4.0	780.
5.0	1000.

The final data cards would be as follows:

Column:	1-10	11-20	21-30	31-40	41-50	51-60	61-70
Card 3	0.0	1.0	2.0	3.0	4.0	5.0	420.
Card 4	500.	10.	125.5	780.	1000.		

APPENDIX B

INPUT PARAMETER COMPUTATION

A. DETERMINATION OF DELTA-H

The program described in Appendix A was used to produce from the path geometry the parameters $d_{L1,2}$, $\theta_{e1,2}$ and Δh. The computation of Δh is only partially computer-aided by the fitting of a straight line to the uncorrected profile heights and subtracting the height of the line from the corresponding terrain height. This difference is output in the array D(I). The interdecile range is then extracted manually from this data by finding the value of the lower boundary of the 90th percentile and subtracting from it the value of the upper boundary of the 10th percentile. An example of the fit of this curve to actual terrain data is shown in the main body of this study.

B. DETERMINATION OF HE1,2

For line of sight paths the following determination was made for effective antenna heights:

1. A straight line is fitted to the corrected terrain profile heights.

2. The line is defined by

$$B(I) = A0 + A1(X(I))$$

in the program defined in Appendix A and should be modified for earth curvature by

$$B'(I) = B(I) - X^2/2A$$

3. The points chosen in the actual profile to which this line is fitted should be only those points which are visible to both transmitter and receiver.

4. The effective antenna height is then the difference between the fitted line and the height of the antenna above sea level.

The procedure described above defines a reflecting plane between the transmitter and receiver.

If, on inspection of the actual terrain and the least square curve, a good fit does not appear to have been obtained due to the roughness of the terrain other methods of obtaining effective antenna heights are available. If the foreground of the antenna represents a good reflecting surface then the antenna height over ground can be used, or multiple least square curves can be used if the path consists of a number of reflecting planes. In the event that terrain characteristics defy this sort of analysis, curves and formulae are available in Annex III to Ref. 5 which provide alternate methods for computing effective height.

The curve to fit terrain is also used in the determination of effective heights for the case of knife edge diffraction which is assumed to occur when the path length is less than the smooth-earth radio horizon for each antenna. In this case two curves are fitted to each of the diffracted paths forming a reflecting plane for each antenna.

For trans-horizon paths the effective heights are obtained by considering the actual height of the antenna above sea level and subtracting from that height the average height of the

terrain between the transmitter and receiver. To illustrate this, consider a link with transmitter height above sea level h_{to}. The heights at N equi-distant points are selected and the mean of the central 80% of these values is computed to produce $\bar{h}_t$ where

$$\bar{h}_t = \frac{1}{.8N} \sum_{i=.1N}^{.9N} h_{ti}$$

e.g., $N = 31$; $\bar{h}_t = \frac{1}{25} \sum_{i=3}^{27} h_{ti}$ $\quad i = 0,1,2,.....,30$

The effective transmitter height is then

$$h_{e1} = h_{to} - \bar{h}_t \quad \text{for} \quad \bar{h}_t \leq h_{to}$$

If the mean value is greater than the height above sea level then the structural height of the antenna above ground is used.

C. DETERMINATION OF DL1,2 and TE1,2

The angular distance θ is readily obtained from the geometry of the profile as shown in Fig. 2. θ_{e1}, and θ_{e2} are measured and θ_e is calculated in the program as the maximum of either $\theta_{e1} + \theta_{e2}$ or $-d_L/a$. The distance d_L is the sum of the distances to the obstacle horizons, d_{L1} and d_{L2}

D. MODIFICATION TO TROPOPLOT

With the above means of determining the parameters $\theta_{e1,2}$, $d_{L1,2}$, TROPOPLOT was modified as follows:

1. Delete the following statements from the main program:

```
      IF (H1G.LE.2.)) GO TO 12
      IF (H1G.GE.2.).OR.H1G.LE.5.)) GO TO 10
      Z1 = 5.0
      GO TO 11
   10 Z1 = 1.0+DSIN(3.1415927*H1G/10.0)
   11 H1E = H1G+Z1*DEXP(-2.0*H1G/DH)
      IF (H2G.LE.2.0) GO TO 15
      IF (H2G.GE.2.0.OR.H2G.LE.5.0) GO TO 13
      Z2 = 5.0
      GO TO 14
   13 Z2 = 1.0+DSIN(3.1415927*H2G/10.0)
   14 H2E = H2G+Z2*DEXP(-2.0*H2G/DH)
   15 CONTINUE
      DL1 = DLS1*DEXP(-.07*DSQRT(DH/DMAX1(5.0,H1E)))
      DL2 = DLS2*DEXP(-.07*DSQRT(DH/DMAX1(5.0,H2E)))
      TE1 = (.00065/DLS1)*((DLS1/DL1-1.)*DH-3.077*H1E)
      TE2 = (.00065/DLS2)*((DLS2/DL2-1.)*DH-3.077*H2E)
```

2. Insert the following statements

```
909 FORMAT (4F10.5)
    READ(5,909) DL1, DL2, TE1, TE2
```

after the statement

```
22 FORMAT (4F10.5).
```

Having accomplished these insertions and deletions the input card deck as shown in Ref. 7 is changed as shown below for user-supplied data only:

First Data Card:

Column 01-10 "Type of Terrain" - Integer

Code: 4 User Terrain Data Used
No data suppression

5 User Terrain Data Used
No "output parameters" printed

Column 11-20 "DB Loss" - Integer

Code: 0 No DB data desired
(omit 2nd data card)

1 DB data desired

Column 21-30 "Distance Between Antennas" - Real
(1-2000) KM

Second Data Card:

Column 01-10 "TX Power Out" (Watts)
Positive Real Number

Column 11-20 "TX Antenna Gain" (db)
Positive Real Number

Column 21-30 "RX Antenna Gain" (db)
Positive Real Number

Column 31-40 "Transmitter Line Loss" (db)
Positive Real Number

Column 41-50 "Required Receiver Line Loss" (db)
Positive Real Number

Column 51-60 "Receiver Sensitivity" (dbm)
Positive Real Number

Third Data Card:

Column 01-10	"Surface Refractivity" Integer (250-400) N-units
Column 11-20	"Surface Conductivity" Real (mhos/meter)
Column 21-30	"Relative Dielectric Constant" Real
Column 31-40	"Interdecile Range" Delta-H

Fourth Data Card:

Column 01-10	"Antenna Polarization" Real
Code: 01.00	Vertical Polarization
Code: -1.00	Horizontal Polarization
Column 11-20	"Frequency" Real (20-40,000)
Column 11-20	"Calculated Antenna Height of Transmitting Antenna" Real (0.5-3000.0) Meters
Column 31-40	"Calculated Antenna Height of Receiving Antenna" Real (0.5-3000.0) Meters

Fifth Data Card:

Column 01-10	"Transmitter Obstacle Horizon, DL1" (km) Real
Column 11-20	"Receiver Obstacle Horizon, DL2" (km) Real
Column 21-30	"Transmitter Elevation (Depression) Angle" (radians) Real Positive (Negative)
Column 31-40	"Receiver Elevation (Depression) Angle TE2" (radians) Real Positive (Negative)

```
C THIS IS A PROGRAM TO PLOT A TERRAIN PATH PROFILE AND COMPUTE                  PR000010
C THE COEFFICIENTS OF A LEAST SQUARE LINE FITTED TO THE PROFILE.               PR000020
C THE DIFFERENCE BETWEEN THE POINTS ON THE LSQ LINE AND THE                    PR000030
C ACTUAL TERRAIN ARE COMPUTED IN THE ARRAY D(I).                               PR000040
C THE TERRAIN PROFILE IS PLOTTED BY THE LOCAL SUBROUTINE                       PR000050
C DRAWP                                                                        PR000060
C                                                                              PR000070
      DIMENSION X(200),Y(200),H(200),E(200),Z(200),B(200),D(200)               PR000080
44    FORMAT(F10.5)                                                            PR000090
C THE FRACTION OF THE EARTH'S RADIUS IS COMPUTED USING                         PR000100
C EITHER THE GRADIENT (TYPE=1.0) OR THE REFRACTIVITY                           PR000110
C (TYPE=2.0)                                                                   PR000120
65    READ (5,44) TYPE                                                         PR000130
111   FORMAT (10X,'TYPE IS:',F10.5)                                            PR000140
      WRITE (6,111) TYPE                                                       PR000150
10    FORMAT (2I5)                                                             PR000160
      INTEGER*4  ITB(12)/12*0/                                                 PR000100
      REAL*4     RTB(28)/28*0.0/                                               PR000110
      IF (TYPE.EQ.1.0) GO TO 55                                                PR000170
      READ (5,10) M,NS                                                         PR000180
      WRITE (6,200) NS                                                         PR000190
      FER=1/(1-(.04665*EXP(.00577*NS)))                                        PR000200
      GO TO 77                                                                 PR000210
55    CONTINUE                                                                 PR000220
      READ (5,88)M,GRAD                                                        PR000230
88    FORMAT(2I5)                                                              PR000240
      FER=1/1-((6.4E-03)*GRAD)                                                 PR000250
32    FORMAT (10X,'THE GRADIENT IS :',F10.5,/)                                 PR000260
      WRITE (6,32) GRAD                                                        PR000270
77    CONTINUE                                                                 PR000280
200   FORMAT(10X,'REFRACTIVE INDEX IS :',I5)                                   PR000290
20    FORMAT (7F10.5)                                                          PR000300
C THE ACTUAL TERRAIN VALUES ARE READ IN FIRST LISTING THE DISTANCE FROM        PR000310
C THE TRANSMITTER IN KM AND THEN THE CORRESPONDING TERRAIN HEIGHTS IN FT       PR000320
C MULTIPLE RUNS CAN BE USED                                                    PR000330
      READ (5,20,END=999)(X(I),I=1,M),(H(I),I=1,M)                             PR000340
      DO 99 I=1,M                                                              PR000350
      XX(I)=X(I)                                                               PR000360
99    CONTINUE                                                                 PR000370
300   FORMAT (10X,'THE DISTANCE FROM XMTR',4X,'HEIGHT ABOVE SEA LEVEL')        PR000380
      WRITE (6,300)                                                            PR000390
400   FORMAT (13X,F10.5,20X,F10.5)                                             PR000400
      R=6370                                                                   PR000410
      WRITE (6,400)((X(I),H(I)),I=1,M)                                         PR000420
30    FORMAT ('1',9X,'PROPAGATION PATH PROFILE',////)                          PR000430
      WRITE (6,30)                                                             PR000440
40    FORMAT (10X,'FRACTION OF EARTH RADIUS IS :',2X,F10.5,////)               PR000450
      WRITE (6,40)  FER                                                        PR000460
```

```
C THE EFFECTIVE EARTH RADIUS 'A' IS COMPUTED                                    PRC00470
      A=FER*R                                                                  PRC00480
      DO 50 I=1,M                                                              PRC00490
C IN THE NEXT TWO STATEMENTS THE ADJUSTED TERRAIN HEIGHT Y(I)                  PRC00500
C AND THE EARTH CURVATURE E(I) ARE COMPUTED                                    PRC00510
      Y(I)=.0003048*H(I)-((X(I)**2)/(2*A))                                     PRC00520
      E(I)=Y(I)-.0003048*H(I)                                                  PRC00530
50    CONTINUE                                                                 PRC00540
60    FORMAT (10X,'HEIGHT',4X,'DISTANCE',4X,'EARTH CURVE',//)                  PRC00550
      WRITE (6,60)                                                             PRC00560
70    FORMAT (7X,F10.5,2X,F10.5,2X,F10.5,/)                                    PRC00570
      WRITE (6,70)((Y(I),X(I),E(I)),I=1,M)                                     PRC00580
C AFTER PRINTING OUT THE VALUES OF Y(I) IN KM AS WELL                          PRC00590
C AS THE VALUE OF EARTH CURVATURE ADJUSTED TO A LINEAR                         PRC00600
C PLOT, THE SPECIFIED INPUT PARAMETERS NECESSARY TO                            PRC00610
C PRODUCE A DRAWING OF THE TERRAIN PROFILE ARE LISTED.                         PRC00620
      ITB(2)=0                                                                 PRC00630
      ITB(3)=6                                                                 PRC00640
      ITB(4)=5                                                                 PRC00650
      ITB(5)=0                                                                 PRC00660
      ITB(6)=0                                                                 PRC00670
      ITB(12)=0                                                                PRC00680
      RTB(3)=0.0                                                               PRC00690
      RTB(4)=0.0                                                               PRC00700
      ITB(1)=1                                                                 PRC00710
      CALL DRAWP (M,XX,Y,ITB,RTB)                                              PRC00570
      ITB(1)=3                                                                 PRC00720
      CALL DRAWP (M,X,E,ITB,RTB)                                               PRC00590
C THE REMAINDER OF THE PROGRAM USES THE UNCORRECTED TERRAIN                    PRC00730
C DATA AND FITS A STRAIGHT LINE TO IT BY LEAST SQUARES.                        PRC00740
C THE LEAST SQUARE LINE IS OUTPUT IN THE FORM OF TWO                           PRC00750
C COEFFICIENTS, A0=THE CONSTANT OR INTERCEPT AND A1=THE SLOPE.                 PRC00760
C THE DIFFERENCE BETWEEN THE ACTUAL TERRAIN HEIGHT FOR A                       PRC00770
C GIVEN X(I) AND THE VALUE FOR THE LINE AT THAT POINT ARE                      PRC00780
C COMPUTED IN THE ARRAY C(I).                                                  PRC00790
      DO 61 I=1,M                                                              PRC00800
      Z(I)=H(I)*.0003048                                                       PRC00810
61    CONTINUE                                                                 PRC00820
71    FORMAT (10X,'HT IN KM',/)                                                PRC00830
      WRITE (6,71)                                                             PRC00840
80    FORMAT (12X,F10.5)                                                       PRC00850
      WRITE (6,80)(Z(I),I=1,M)                                                 PRC00860
      SUMX=0                                                                   PRC00870
      SUMY=0                                                                   PRC00880
      SUMXY=0                                                                  PRC00890
      SMXSQ=0                                                                  PRC00900
      A0=0                                                                     PRC00910
      A1=0                                                                     PRC00920
```

```
      DO 90 I=1,M                                                       PRG00930
      SUMX=X(I)+SUMX                                                    PRG00940
90    CONTINUE                                                          PRG00950
100   FORMAT (10X,'SUMX =',F14.5)                                       PRG00960
      WRITE (6,100) SUMX                                                PRG00970
      DO 210 I=1,M                                                      PRG00980
      SUMY=Z(I)+SUMY                                                    PRG00990
210   CONTINUE                                                          PRG01000
201   FORMAT (10X,'SUMY =',F10.5)                                       PRG01010
      WRITE (6,201) SUMY                                                PRG01020
      DO 310 I=1,M                                                      PRG01030
      SUMXY=(X(I)*Z(I))+SUMXY                                           PRG01040
310   CONTINUE                                                          PRG01050
301   FORMAT (9X,'SUMXY =',F10.5)                                       PRG01060
      WRITE (6,301) SUMXY                                               PRG01070
      DO 410 I=1,M                                                      PRG01080
      SMXSQ=(X(I)**2)+SMXSQ                                             PRG01090
410   CONTINUE                                                          PRG01100
401   FORMAT (9X,'SMXSQ =',F14.5)                                       PRG01110
      WRITE (6,401) SMXSQ                                               PRG01120
      DENOM=(M*SMXSQ)-(SUMX**2)                                         PRG01130
402   FORMAT (10X,'THE DENOMINATOR IS :',F14.5,//)                      PRG01140
      WRITE (6,402) DENOM                                               PRG01150
      AO=((SUMY*SMXSQ)-(SUMX*SUMXY))/DENOM                              PRG01160
500   FORMAT (10X,'THE CONSTANT TERM IS :',F10.5)                       PRG01170
      WRITE (6,500) AO                                                  PRG01180
      A1=((M*SUMXY)-(SUMX*SUMY))/DENOM                                  PRG01190
501   FORMAT (10X,'THE COEFFFICIENT OF X IS =',F10.5)                   PRG01200
      WRITE (6,501) A1                                                  PRG01210
      DO 600 I=1,M                                                      PRG01220
      B(I)=AO+A1*X(I)                                                   PRG01230
      D(I)=ABS(Z(I)-B(I))                                               PRG01240
600   CONTINUE                                                          PRG01250
601   FORMAT (10X,'DISTANCE',4X,'DIFFERENCE',/)                         PRG01260
      WRITE(6,601)                                                      PRG01270
602   FORMAT (9X,F10.5,4X,F10.5)                                        PRG01280
      WRITE (6,602)((X(I),D(I)),I=1,M)                                  PRG01290
      GO TO 65                                                          PRG01300
555   CONTINUE                                                          PRG01310
      STOP                                                              PRG01320
      END                                                               PRG01330
```

LIST OF REFERENCES

1. Bullington, K., "Radio Propagation Fundamentals, "Bell System Technical Journal, v. 36, pp. 593-626, May 1957.

2. Panter, P. F., Communications Systems Design, pp. 371-405, McGraw-Hill, 1972.

3. Picquenard, A., Radio Wave Propagation, Wiley, 1974.

4. Naval Electronics Systems Command, Naval Shore Electronics Criteria, May 1972.

5. National Bureau of Standards Technical Note No. 101, Transmission Loss Predictions for Tropospheric Communications Circuits, by Rice, P. L., Longley, A. G., Norton, K. A. and Barsis, A. P., v. 1, 2, 7 May 1965.

6. ESSA Technical Report ERL 79-7TS-67, Prediction of Tropospheric Radio Transmission Loss Over Irregular Terrain, A Computer Method, by Longley, A. G., and Rice, P. L., July 1968.

7. Callaghan, J. M., "TROPOPLOT" an Improved Fortran Computer Program for Prediction of Long-Term Median Tropospheric Radio Transmission Loss Over Irregular Terrain, M.S. Thesis, U.S. Naval Postgraduate School, 1973.

8. ESSA Technical Report ERL 148-1%S 97, Comparison of Propagation Measurements with Predicted Values in the 20 to 10,000 MHz Range, by Longley, A. G. and Reasoner, R. K., January 1970.

9. National Bureau of Standards Monograph No. 22, Climatic Charts and Data of the Radio Refractive Index for the United States and the World, by Bean, B., Horn, J. and Ozanich, A. M., 1960.

10. Hitney, H. V. and Richter, J. H., "Integrated Refractive Effects Prediction System (IREPS)" Naval Engineers Journal, v. 88, April 1976.

11. National Bureau of Standards Monograph 92, Radio Meteorology, by Bean, B. R. and Dutton, E. J., 1 March 1966.

12. Du Castel, F., Tropospheric Radiowave Beyond the Horizon, Perganon Press, 1966.

13. ITT, Reference Data for Radio Engineers, 12th ed., Ch. 26, 1975.

14. Sherar, R. C. and Rosenthal, J., "Don't Fall Into the Radar Hole," Proceedings of the Naval Institute, pp. 55-66, December 1973.

15. Freeman, R. L., Telecommunication Transmission Handbook, pp. 177-197, Wiley 1975.

16. Jordan, E. C. and Balmain, K. G., Electro-Magnetic Waves and Radiating Systems, Prentice-Hall, 1968.

DISTRIBUTION LIST

		No. Copies
1.	Defense Documentation Center Cameron Station Alexandria, VA 22314	2
2.	Library, Code 0212 Naval Postgraduate School Monterey, CA 93940	2
3.	Assoc. Professor J. B. Knorr, Code 52Ko Department of Electrical Engineering Naval Postgraduate School Monterey, CA 93940	1
4.	Department Chairman, Code 52 Department of Electrical Engineering Naval Postgraduate School Monterey, CA 93940	1
5.	Assoc. Professor R. W. Adler, Code 52Ad Department of Electrical Engineering Naval Postgraduate School Monterey, CA 93940	1
6.	Commanding Officer Naval Torpedo Station Attn: Dr. W.A. Middleton, Code 702 Keyport, WA 98345	1
7.	Mr. H. V. Hitney, Code 2220 Naval Electronics Laboratory Center 271 Catalina Blvd. San Diego, CA 92152	1
8.	Commanding Officer Naval Shipyard Attn: LCDR J. M. Callaghan, Code 106 Philadelphia, PA 19112	1
9.	LT R. M. Cassidy 3716 Forest Grove Dr. Annandale, VA 22003	2
10.	Commanding Officer Naval Torpedo Station Attn: Mr. Andy Hooper, Code 813A Keyport, WA 98345	1